

DRM-Rackmount Frame



Mini-Converter related details for use in the DRM

Mini-Converter	Max Power Consumption	Dimensions (W x D x H)	How Many Fit per DRM-R2*
3G-AM	5 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	6
3G-AMA	5 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	6
3GDA	3 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	6
12G-AM	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AM-R	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AM-R-ST	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AM-T	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AM-T-ST	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AM-TR	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AMA	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AMA-R	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AMA-R-ST	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AMA-T	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AMA-T-ST	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12G-AMA-TR	10 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	5
12GDA	3 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	6
12GM	12 watts	5.76" x 4.02" x 0.90" (146.31 x 102.11 x 22.86 mm)	4
ADA4	3 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	6
C10DA	2 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	6
FiDO-2R	3 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-2R-12G	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-2R-MM	3 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-2T	3 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-2T-12G	3.5 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-2T-MM	3 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-4R	5 watts	4.60" x 4.02" x 0.85" (117.00 x 102.11 x 21.60 mm)	6
FiDO-4R-MM	5 watts	4.60" x 4.02" x 0.85" (117.00 x 102.11 x 21.60 mm)	6
FiDO-4R-ST	4 watts	5.80" x 3.90" x 0.80" (147.00 x 99.00 x 20.00 mm)	6
FiDO-4T	5 watts	4.60" x 4.02" x 0.85" (117.00 x 102.11 x 21.60 mm)	6
FiDO-4T-MM	5 watts	4.60" x 4.02" x 0.85" (117.00 x 102.11 x 21.60 mm)	6
FiDO-4T-ST	4 watts	5.80" x 3.90" x 0.80" (147.00 x 99.00 x 20.00 mm)	6

* Note: Maximum of this particular Mini-Converter, power consumption of all Mini-Converters can not exceed 50 watts in the DRM.

DRM-Rackmount Frame



Mini-Converter related details for use in the DRM

Mini-Converter	Max Power Consumption	Dimensions (W x D x H)	How Many Fit per DRM-R2*
FiDO-R	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-R-12G	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-R-12G-ST	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-R-MM	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-R-SC	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-R-ST	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-T	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-T-12G	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-T-12G-ST	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-T-MM	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-T-SC	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-T-ST	2 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-TR	3 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-TR-12G	4 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FiDO-TR-MM	3 watts	4.60" x 1.71" x 0.85" (117.00 x 43.50 x 21.60 mm)	12
FS-Mini	7 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	6
GEN10	2 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	6
HA5-12G	11 watts	4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm)	4
HA5-12G-T	11 watts	4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm)	4
HA5-12G-T-ST	11 watts	4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm)	4
HA5-4K	10 watts	5.76" x 4.02" x 0.90" (146.31 x 102.11 x 22.86 mm)	5
HA5-Fiber	4.5 watts	4.40" x 2.40" x 1.00" (112.00 x 61.00 x 25.00 mm)	10
HA5-Plus	7.5 watts	4.60" x 2.40" x 1.00" (116.84 x 60.96 x 25.4 mm)	6
HD5DA	2.5 watts	5.80" x 2.40" x 1.00" (131.00 x 61.00 x 25.00 mm)	12
HDP3	6.5 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	6
Hi5-12G	11 watts	4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm)	4
Hi5-12G-R	11 watts	4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm)	4
Hi5-12G-R-ST	11 watts	4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm)	4
Hi5-12G-TR	11 watts	4.60" x 4.02" x 0.90" (116.84 x 102.11 x 22.86 mm)	4

* Note: Maximum of this particular Mini-Converter, power consumption of all Mini-Converters can not exceed 50 watts in the DRM.

DRM-Rackmount Frame



Mini-Converter related details for use in the DRM

Mini-Converter	Max Power Consumption	Dimensions (W x D x H)	How Many Fit per DRM-R2*
Hi5-4K-Plus	12 watts	5.76" x 4.02" x 0.90" (146.31 x 102.11 x 22.86 mm)	4
Hi5-Fiber	3 watts	4.60" x 2.40" x 1.00" (116.84 x 60.96 x 25.40 mm)	12
Hi5-Plus	7.5 watts	4.60" x 2.40" x 1.00" (117.00 x 61.00 x 25.00 mm)	6
IPR-10G2-HDMI	13 watts	5.07" x 0.94" x 5.06" (128.80 x 23.90 x 128.40 mm)	3
IPR-10G2-SDI	13 watts	5.07" x 0.94" x 5.06" (128.80 x 23.90 x 128.40 mm)	3
IPT-10G2-HDMI	13 watts	5.07" x 0.94" x 5.06" (128.80 x 23.90 x 128.40 mm)	3
IPT-10G2-SDI	13 watts	5.07" x 0.94" x 5.06" (128.80 x 23.90 x 128.40 mm)	3
ROI-DP	7 watts	5.77" x 4.02" x 0.90" (146.56 x 102.11 x 22.86 mm)	6
ROI-DVI	8 watts	5.77" x 4.02" x 0.90" (146.56 x 102.11 x 22.86 mm)	6
ROI-HDMI	8 watts	5.77" x 4.02" x 0.90" (146.56 x 102.11 x 22.86 mm)	6
ROI-SDI	7 watts	5.77" x 4.02" x 0.90" (146.56 x 102.11 x 22.86 mm)	6
UDC	7 watts	5.80" x 3.10" x 1.00" (147.32 x 78.74 x 25.40 mm)	6
V2Analog™	3 watts	5.10" x 2.40" x 1.00" (129.54 x 60.96 x 25.40 mm)	12
V2Digital™	3 watts	5.10" x 2.40" x 1.00" (129.54 x 60.96 x 25.40 mm)	12

* Note: Maximum of this particular Mini-Converter, power consumption of all Mini-Converters can not exceed 50 watts in the DRM.